

# DELTA MOBILE RADIO CABLES

By: Mark A. Cobbeldick, KB4CVN

CONTROL UNIT	MODEL RADIO	OLD (UNSHIELDED) CABLE	LEADS #	NEW (SHIELDED) CABLE	LEADS #	LENGTH
C-600 & S-600	CRYSTAL DELTA (2-CHANNELS MAX) & SYN DELTA 1-CHANNEL (up to 3-CHANNEL MAX)	19D900436G1	18	19D901740G3	30	3 METERS (9'10")
		19D900436G2	18	19D901740G3	30	3 METERS (9'10")
		19D900436G3	18	19D901740G1	30	6 METERS (19'8")
		19D900436G4	18	19D901740G1	30	6 METERS (19'8")
		19D900436G5	18	19D901740G2	30	9 METERS (29'6")
		19D900436G6	18	19D901740G2	30	9 METERS (29'6")
C-600 & S-600	CRYSTAL DELTA (4-CHANNELS MAX) & SYN DELTA (2-MODES OF 8-CHANNELS)	19D900436G7	30	19D901740G3	30	3 METERS (9'10")
		19D900436G8	30	19D901740G3	30	3 METERS (9'10")
		19D900436G9	30	19D901740G1	30	6 METERS (19'8")
		19D900436G10	30	19D901740G1	30	6 METERS (19'8")
		19D900436G11	30	19D901740G2	30	9 METERS (29'6")
		19D900436G12	30	19D901740G2	30	9 METERS (29'6")
S-500 & S-550	SYN DELTA (2-MODES OF 32-CHANNELS) & GE-MARC V (REAR-MOUNT)	19D900447G1	35	19D901739G5	35	3 METERS (9'10")
		19D900447G2	35	19D901739G5	35	3 METERS (9'10")
		19D900447G3	35	19D901739G1	35	6 METERS (19'8")
		19D900447G4	35	19D901739G1	35	6 METERS (19'8")
		19D900447G5	35	19D901739G2	35	9 METERS (29'6")
		19D900447G6	35	19D901739G2	35	9 METERS (29'6")
MASTR2 ADAPTER	19D900447G7	REQUIRED DECIMAL TO BINARY CONVERTER FOR MULTI-FREQUENCY OPERATION.			18"	
P1	19D900447G8	REPLACEMENT CONNECTOR FOR RADIO END OF CABLE				
MASTR2 ADAPTER	19D900447G9	REQUIRED DECIMAL TO BINARY CONVERTER FOR MULTI-FREQUENCY OPERATION.			3 METERS (9'10")	
		<b>LONG GROUND LEAD</b>				
		USE 19A136690G1 KIT TO INCREASE THE BLACK GROUND LEAD LENGTH (33 FEET)				
		PART WAS <u>NEVER</u> LISTED IN SERVICE PARTS				

# DELTA MOBILE RADIO CABLES

CONTROL UNIT	MODEL RADIO	OLD (UNSHIELDED) CABLE	LEADS #	NEW (SHIELDED) CABLE	LEADS #	LENGTH
S-500 & S-550	SYN DELTA (3-CHANNELS)	19D900447G10	18	19D901739G5	18	3 METERS (9'10")
		19D900447G11	18	19D901739G5	18	3 METERS (9'10")
		19D900447G12	18	19D901739G1	18	6 METERS (19'8")
		19D900447G13	18	19D901739G1	18	6 METERS (19'8")
		19D900447G14	18	19D901739G2	18	9 METERS (29'6")
		19D900447G15	18	19D901739G2	18	9 METERS (29'6")
S-825 S-950 S-990	ALL MODELS	19D900447G16	36	19D901739G5	36	3 METERS (9'10")
		19D900447G17	36	19D901739G5	36	3 METERS (9'10")
		19D900447G18	36	19D901739G1	36	6 METERS (19'8")
		19D900447G19	36	19D901739G1	36	6 METERS (19'8")
		19D900447G20	36	19D901739G2	36	9 METERS (29'6")
		19D900447G21	35	19D901739G2	36	9 METERS (29'6")
GE MARC V	MINITURE	19D900447G22	35			3 METERS (9'10")
	CLASSIC	19D900447G23	35			6 METERS (19'8")
	REMOTE	19D900447G24	35			9 METERS (29'6")

**LONG GROUND LEAD**

**USE 19A136690G1 KIT TO INCREASE THE BLACK GROUND LEAD LENGTH (33 FEET)**

**PART WAS NEVER LISTED IN SERVICE PARTS**

## Other Cables:

Ignition Cable	19B226516G3	
Dual-Control Cable	19D423424G13	3 METERS (9'10")
Dual-Control Cable	19D423424G14	6 METERS (19'8")
Dual-Control Cable	19D423424G15	9 METERS (29'6")